


TMA2124F03V5-1D

TWIN TMA 1900/AWS/LOWPASS 555-960MHZ 6 ANT

NON-DIPLEXED 1900/AWS ANTENNA PORTS

Designed to be deployed in co-located AWS & 1900 networks, the Kaelus TMA2124 provides gain in 1900 and AWS uplink, using independent LNAs per band and per channel. Low loss bypass 555-960MHz signal to low band antennas is also provided.



FEATURES

- Improved base station sensitivity through excellent noise figure performance and linearity
- AISG 2.0 compatible, full software upgradable using AISG “personality” upload
- DC/AISG passthrough to AWS antenna (port 5)
- AISG OUT connector disabled when AISG device (SBT equipped antenna) present on Port 3 +R1/+R1
- One AISG subunit per LNA, 4 in total. All fixed gain
- 555-960 bypass to low band antenna

TECHNICAL SPECIFICATIONS

BAND NAME	1900	AWS
DOWNLINK		
Passband	1930 - 1990MHz	2110 - 2200MHz
Insertion loss	0.4dB typical	0.3dB typical
Return loss	22dB typical	
Maximum input power	160W (average) / 2kW (PEP)	160W (average) / 2kW (PEP)
Intermodulation products	-155dBc maximum, at antenna port in RX band with 2 x 20W carriers	-163dBc maximum, at antenna port in RX band with 2 x 20W carriers
UPLINK		
Passband	1850 - 1910MHz	1695 - 1780MHz
Gain	13dB	
Gain variation	±1dB maximum	
Return loss	22dB typical	
Bypass return loss	14dB typical	
Bypass loss	3dB typical	
Noise figure	1.2dB typical @ 13dB gain	1.0dB typical @ 13dB gain
Output IP3	+28dBm typical	
Maximum input power with no damage	+12dBm	
555-960 LOWPASS FILTER		
Passband	555 - 960MHz	
Insertion loss	0.2dB typical	
Return loss	21dB typical	
Maximum input power	250W (average) / 2.5kW (PEP)	
Intermodulation products	-155dBc maximum, at antenna port with 2 x 20W carriers	
ELECTRICAL		
Impedance	50Ohms	

POWER SUPPLY AND ALARM (CURRENT WINDOW ALARM MODE, DEFAULT)

Current window alarm mode (CWA) is the default operating mode and can be configured to specific customer requirements. The TMA2124F03V4 is configured so that both channels are independently powered and monitored via their respective BTS port, 7 or 8. The BTS port sinks additional current to indicate an alarm state in its uplink path. Normal operating and alarm current values are configured independently via a field-loadable personality file. Please contact Kaelus for more information.

DC supply voltage	+8.5 to +18V DC, case is DC ground
DC supply	Each BTS port powered individually
DC supply current, normal mode	200mA per port typical (both ports are powered)
DC supply current, alarm mode	300mA per port typical (both ports are powered)

AISG MODE OF OPERATION (AUTO SELECTED ON VALID AISG 2.0 FRAMES)

AISG signals can be applied to port 7 or port 8. The TMA unit switches to AISG mode when valid frames are detected on either port 7 or 8. All LNAs take DC power from the port with the AISG frames or, if DC is present on both ports, power will be supplied equally between the ports. Each LNA is controlled uniquely by its sub-unit number.

DC supply voltage	+7.5V to +30V DC
AISG version	2.0 (1.1 optional)
Supply current, AISG mode	500mA @ 7.5V, 135mA @ 30V typical
AISG connector, current rating	IEC60130-9, 8-pin female, < 4A peak, 2A continuous, pin 6
Field firmware upgradable	Yes (R951022ATA2.0 Rev 2.9.12)
AISG pass through to antenna port	Yes

ANTENNA AISG OOK + DC

When DC is applied it is quickly switched through to port 5. If an over-current condition is detected, DC & AISG are disconnected from port 5. If DC remains connected to the load at port 5, DC and AISG are disconnected from the AISG OUT 8 pin connector. If DC is disconnected from port 5, DC and AISG are enabled at the AISG OUT 8 pin connector. If a short circuit is detected at the AISG OUT 8 pin connector, DC and AISG are disabled.

Mode of Operation	Voltage at Port 5	Assumption	"Autosense + Protection" Switch Status	Comment
AISG or CWA	High	Device present or open circuit	Close	DC & AISG OOK will be supplied to port 5. DC & AISG is removed from the AISG OUT 8 pin port
AISG or CWA	Low	DC short circuit or low DC resistance	Open	DC & AISG OOK will not be supplied to port 5. DC & AISG are supplied to the AISG OUT 8 pin port

ENVIRONMENTAL

For further details of environmental compliance, please contact Kaelus.

Temperature range	-40°C to +65°C -40°F to +149°F
Ingress protection	IP67
Altitude	3,000m 10,000ft
Lightning protection	IEC61312-1, RF: ±5kA maximum (8/20us), AISG: ±2kA maximum (8/20us)
MTBF	>1,000,000 hours
Compliance	FCC Part 15 subpart B


MECHANICAL

Dimensions H x D x W	245 x 128 x 210mm 9.65 x 5.04 x 8.27in Excluding connectors
Weight	8.1kg 17.86lbs
Finish	Painted, light grey (RAL 7035)
Connectors	4.3-10 (F) x 8 long neck, AISG (F) x 1
Wind Load	Front 390N, Side 147N (Single) Front 251N, Side 409N (Twin) At 74m/s (AS/NZS 1170-2-2011 Structural design - Wind actions - Cyclone areas)
Mounting	Pole/wall bracket supplied with two metal clamps 45-178mm diameter poles

ORDERING INFORMATION

PART NUMBER	CONFIGURATION	OPTIONAL FEATURES	CONNECTORS
TMA2124F03V5-1D	TWIN 2 in / 6 out	STANDARD	4.3-10 (F)
TMA2124F03V5-2D	QUAD 4 in / 12 out	STANDARD	4.3-10 (F)
TMA2124F03V5-1S	TWIN 2 in / 6 out	STANDARD	4.3-10 (F)
TMA2124F03V5-2S	QUAD 4 in / 12 out	STANDARD	4.3-10 (F)

ELECTRICAL BLOCK DIAGRAM



MECHANICAL BLOCK DIAGRAM

